

Automatic Voltage Regulator

1200VA
600W

Alfa Digital PSE -1200

Features:

- 6pc Outlets Design to Protect Peripheral Devices
- Automatically Regulating High Voltage and Low Voltage
- Internet, ADSL, Tel/Fax Data Line Surge Protection
- Able to Reset Input Overload Protection Circuit Breaker
- User-friendly Visual Indicators Display
- Wires Collection
- Child Protector
- Wall Mount Holes
- Ceramic Arrestor to Protect Coaxial Cable Line



Introduction:



Surge Protection

- **Boost LED:** LED lights when the AVR is correcting a low utility voltage condition.
- **Power On LED:** LED lights when the AVR is supplying utility power to the loads.
- **Buck LED:** LED lights when the AVR is correcting a high utility voltage condition.

AVR Protection

• **Child Protection:** To prevent children from inserting any electric conducted object and getting hurt.

• **Wires Collection:** To collect wires in AVR cabinet.

All wires connected on VAR can be well-organized to make your home & office look neat and clean.

Main ON/OFF Switch

AVR turn on & turn off.

Allowing easy recovery from an overload.

• **Coax Surge Protection (Optional):** Ceramic arrester to protect coaxial cable line for TV, VCR, Audio System

AC Input

SPECIFICATION

Capacity	1200VA - 600W			
AC Input	Normal Voltage	220/230/240VA	Input Voltage Range	161VAC ~ 288VAC (-30%+25%)
	Phase	1 Phase 2 Wires	Frequency	50Hz
AC Output	Output Voltage Range	207VAC ~ 253VAC (+/-10%)	Frequency	50Hz
DC Output	Output Voltage Range	5 VDC (+/-2%) (Optional)		
Outlets	AVR/Surge only	3/3		
Protection	Network Surge Suppression	RJ-45/RJ-11	Overload	Manual Reset Circuit Switch
	Short Circuit	Manual Reset Circuit Switch		
LED	Power On/Off	Green LED	Boost Yellow LED	Buck Yellow LED
Physical	Dimension (D*W*H)	263*120*85mm	Net Weight	2.3Kgs
Warranty	1 Year			

THE COMPLETE PROTECTION

